



FEATURES & SPECIFICATIONS

INTENDED USE — The PS730L multi-volt (120V thru 277V; 50-60Hz) emergency LED driver is designed to provide a minimum of 90 minutes of illumination for LED luminaires during the loss of normal AC power. It is UL classified for field installation in specified luminaires and UL recognized for factory installation inside indoor, damp or sealed and gasketed wet location listed LED luminaires utilizing 7-watts maximum output power, 30VDC maximum output voltage and an output current of 230 mA.

CONSTRUCTION — UL rated, painted steel enclosure. U.S. Patent No. 6,522,147; 6,577,136.

PERFORMANCE — When normal AC power fails, the PS730L immediately drives the LED load at a reduced light output for a minimum of 90 minutes. When AC power is present, the emergency LED driver operates in various charging modes to ensure the sealed, maintenance-free, high-temperature nickel-cadmium batteries are fully recharged within 24 hours after a discharge and remains fully charged until the next loss of AC power. The pilot light/test switch provides visual and manual means of monitoring the system operation.

ELECTRICAL — Multi-volt input capability – 120V thru 277V; 50-60Hz

Output current – 230 mA

Maximum Output Voltage – 30 VDC

Maximum Output Power – 7 watts

Maximum AC input – 290 mA and 3.3 watts

INSTALLATION — Mounts concealed within fixture wireway for clean appearance and protection against vandalism; or mounts on outside of fixture housing if internal space is limited. One 1/2" holes in fixture channel permit mounting of test switch/pilot light behind fixture lens

Compact size (16.7" L x 1.19" W x 1.18" H) fits in a variety of LED fixtures: troffers, volumetric recessed, industrials, commercials and strips

Unit wires two ways: on night light circuit (permanently energized) or on switchable circuit (unswitched circuit to battery charger and switched circuit to the fixture driver).

Ambient temp ratings - 0 °C to 50 °C (32 °F to 122 °F)

Polarized quick-connect pilot light / test switch assembly simplifies installation

Standardized mounting centers

LISTINGS — UL recognized. Meets UL 924, NFPA 101 (current Life Safety Code), NEC and OSHA illumination standards

Standard unit is UL recognized for installation in damp or wet location sealed and gasketed listed luminaires

Not suitable for mounting outside the luminaire in a wet location application

UL classified for field installation in the following ABL fixture families: SPM9L, BRM9L and BRW9L

WARRANTY — 5-year limited warranty. Complete warranty terms located at www.acuitybrands.com/CustomerResources/Terms_and_conditions.aspx

Note: Actual performance may differ as a result of end-user environment and application. Specifications subject to change without notice.

| |
|----------------|
| Catalog Number |
| Notes |
| Type |


PS730L

Euro-stick Profile LED Emergency Battery Backup



MOUNTING

All dimensions are in inches



Cross section end view

Length: 16.7 inches

Shipping weight: 2.0 lbs (0.68 kg).

Euro-stick profile design fits in the tightest of applications

How to Calculate Delivered Lumens in Emergency Mode

Use the formula below to determine the delivered lumens in emergency mode

Delivered Lumens = 1.25 x P x LPW

P = Output power of emergency driver. P = 7W for PS730L

LPW = Lumen per watt rating of the luminaire. This information is available on the ABL luminaire spec sheet.

The LPW rating is also available at Designlight Consortium.

ORDERING INFORMATION

Lead times will vary depending on options selected. Consult with your sales representative.

Example: PS730L

| PS730L | |
|---------------------|--|
| Series | Options |
| PS730L Power Sentry | SD Self-diagnostics ¹ FIK Field install kit FIKRE Field install kit with remote enclosure |

| Accessories ² : Order as separate catalog number. | |
|--|--|
| ELA TSPLP | Remote or replacement test switch pilot light; mounts up to 25' away from fixture |
| ELA TSPLPSD | Remote or replacement test switch pilot light for self-diagnostics; mounts up to 25' away from fixture |
| ELA PSMKSD | External mounting kit for self-diagnostics module (2 required per module) |
| ELA PSRME IC | Remote enclosure |

Notes

- 1 Self-diagnostics (PSSD2) module ships separately. See [PSSD2](#) Accessories spec sheet for details on self-diagnostics.
- 2 See Accessories specification sheets for details on other compatible devices ELA-RTS-TSPLP-PSTS-PSPRSB and ELA-PSMK-PSMKSD-PSDMT-PSRME

PS730L LED Emergency Battery Backup

SPECIFICATIONS

| BATTERY | | | | |
|-----------------------|-------------------------|----------------------------|-------------------|----------------------------------|
| Sealed Nickel-Cadmium | | | | |
| Voltage | Shelf life ¹ | Expected life ¹ | Maintenance | Ambient temperature ² |
| 4.8V | 3 years | 7-10 years | none ³ | 0-50C (32-122° F) |

Notes

- 1 At 77°F Ambient temperature, charge/discharge cycles and prolonged full discharge may reduce useful life.
- 2 Ambient temperature range where unit will provide capacity for 90 minutes. Higher and lower temperatures affect life and capacity. Consult factory for detailed information.
- 3 All life safety equipment, including emergency lighting for path of egress must be tested in accordance with all National Fire Protection Association (NFPA) and local codes. Failure to perform the required testing could jeopardize the safety of occupants and will void all warranties.

KEY OPTIONS

Self Diagnostics Module PSSD2



PS730L