



# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

## DEDICATED 120V ONLY HOUSING

**Incandescent and Magnetic Low Voltage - Forward Phase Dimming**

- Dimmable with the use of most forward phase dimmers • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL) Factor = 50% (.5)  
 (600/10) X .5 = 30 Fixtures per Dimmer

**Electronic Low Voltage - Reverse Phase Dimming**

- Dimmable with the use of most electronic low voltage dimmers • Electronic low voltage dimmers require a neutral wire in the wall box • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL) Factor = 75% (.75)  
 (600/10) X .75 = 45 Fixtures per Dimmer

## UNIVERSAL VOLTAGE

Universal Voltage (120-277V) Housings

0-10V Dimming Control

- Dimming range of 100% down to 10% or lower with a minimum load of one fixture.

† Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)

Note: C-Bus is 25 fixtures per channel.

### Juno Qualified Dimmers

| Fixture Series   | Lutron® Model Numbers:  | Leviton® Model Numbers:                                       | Whole House Integrated Control Systems:  | Lutron® Model Numbers:  | Leviton® Model Numbers:                      | Lutron® Model Numbers:  | Leviton® Model Numbers:     | Whole House Integrated Control Systems:  |
|--|---|---|--|---|--|---|-----------------------------|--|
| 600 LUMEN LED DOWNLIGHT AND RETROFIT<br>WARMDIM®<br>IC 4", 5" and 6" Generation 4N Series    | Ariadni® AY*<br>Ceana® CNLV*<br>Diva® DV*/DVLV* Series<br>Glyder® GLV Series*<br>Nova T® NT Series<br>Nova T® NTLV*<br>Rotary D* Series<br>Skylark® S*<br>Skylark® SLV* Series<br>Toggle® TG*   | IlumaTech™ IPL06 Series<br>Sureslide 6613*<br>Sureslide 6633* | Lutron® GRAFIK Eye QSGR-RP*<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® LP-RPM-4U*<br>Lutron® Homeworks® QS HQRD-10ND<br>Lutron® Radio RA2® RRD-10ND   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IlumaTech™ IPE04<br>Vizia VPE06-1LX*         |   |                             |  |
| 600 LUMEN LED DOWNLIGHT AND RETROFIT<br>WARMDIM®<br>IC 4", 5" and 6" Generation 3 & 4 Series | Ariadni® AY*/AYCL Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVCL*/DVLV* Series<br>Glyder® GLV Series*<br>Lumea® LGCL Series<br>Nova T® NT*/NTLV* Series<br>Rotary D Series<br>Skylark® Contour CTCL Series<br>Skylark® S/SLV* Series<br>Spacer System® SPSLV Series<br>Toggle® TGCL Series | IlumaTech™ IPL06 Series<br>Trimatron 6681*                    | Lutron® Homeworks® QS HQRD-10ND<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND<br>Lutron® Radio RA2® RRD-6D<br>Lutron® Radio RA2® RRD-6NA*<br>Schneider Electric C-Bus SLC5504TD4A*                           | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IlumaTech™ IPE04*                            |   |                             |  |
| 600 LUMEN LED DOWNLIGHT<br>IC 4" IC1ALED/IC1RALED<br>Generation 4N Series                    | Ariadni® AY*/AYCL* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVCL*/DVLV* Series<br>Glyder® GLV Series*<br>Lumea® LGCL* Series<br>Nova T® NT Series<br>Nova T® NTLV* Series<br>Rotary D* Series<br>Skylark® Contour CTCL* Series<br>Skylark® S*/SLV* Series<br>Toggle® TGCL* Series         | IlumaTech™ IPL06 Series<br>Sureslide 6613*<br>Sureslide 6633* | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP*<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA*                                  | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IlumaTech™ IPE04* Series<br>Vizia VPE06-1LX* | Diva® DVTV Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV Series <sup>1</sup><br>Nova® NFTV Series <sup>1</sup>    | IlumaTech™ IP710-DLX Series | Lutron® Homeworks® GRX-TVM2<br>Wattstopper LMRC-211*<br>Crestron DIN-4DIMFLV4  |
| 600 LUMEN LED DOWNLIGHT<br>IC 4", 5" and 6" Generation 4 Series                              | Ariadni® AY*/AYCL* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVCL*/DVLV* Series<br>Glyder® GLV Series*<br>Lumea® LGCL* Series<br>Nova T® NT Series<br>Nova T® NTLV* Series<br>Rotary D* Series<br>Skylark® Contour CTCL* Series<br>Skylark® S*/SLV* Series<br>Toggle® TGCL* Series         | IlumaTech™ IPL06 Series<br>Sureslide 6613*<br>Sureslide 6633* | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP*<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® LP-RPM-4U<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA*  | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IlumaTech™ IPE04* Series<br>Vizia VPE06-1LX* | Diva® DVTV Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV Series <sup>1</sup><br>Nova® NFTV Series <sup>1</sup>    | IlumaTech™ IP710-DLX Series | Schneider Electric C-Bus SLCLE5504TAMP*<br>Lutron® Homeworks® GRX-TVM2         |
| 700 LUMEN LED DOWNLIGHT<br>4" IC4AL (07LM), IC4RAL (07LM), TC4RAL (07LM)                     | Ariadni® AY* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV* Series<br>Glyder® GLV* Series<br>Nova T® NTLV* Series<br>Rotary D Series<br>Skylark® S*/SLV* Series   | IlumaTech™ IPL06* Series<br>Sureslide 6613*<br>Sureslide 6633 | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP<br>Lutron® Homeworks® LP-RPM-4A*<br>Lutron® Homeworks® LP-RPM-4U*<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA* | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IlumaTech™ IPE04* Series<br>Vizia VPE06-1LX* | Diva® DVTV* Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV* Series <sup>1</sup><br>Nova® NFTV* Series <sup>1</sup> | IlumaTech™ IP710-DLX Series | Lutron® Homeworks® GRX-TVM2*<br>Wattstopper LMRC-211*<br>Crestron DIN-4DIMFLV4 |
| 600 LUMEN LED DOWNLIGHT<br>IC 4", 5" and 6" Generation 3† Series                             | Ariadni® AY*/AYCL Series<br>Ceana® CNLV Series<br>Diva® DV*/DVCL*/DVLV Series<br>Glyder® GLV Series<br>Lumea® LGCL Series<br>Nova T® NT/NTLV Series<br>Skylark® Contour CTCL Series<br>Skylark® S/SLV Series<br>Toggle® TG/TGCL Series  | IlumaTech™ IPL06 Series<br>Trimatron 6681                     | Lutron® Homeworks® QS HQRD-6NA<br>Lutron® Radio RA2® RRD-10ND<br>Lutron® Radio RA2® RRD-6NA<br>Schneider Electric C-Bus SLC5504TD4A  | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series |  | Diva® DVTV Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV Series <sup>1</sup><br>Nova® NFTV Series <sup>1</sup>    | IlumaTech™ IP710-DLX Series | Schneider Electric C-Bus SLCLE5504TAMP*<br>Lutron® Homeworks® GRX-TVM2         |

\* Juno recommended dimmers  
 Consult technical services for additional information regarding other dimmer model qualification.



# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

|  |          | DEDICATED 120V ONLY HOUSING   |   |   |   | UNIVERSAL VOLTAGE  |   |  |
|--|----------|---|---|---|---|--|---|--|
|  |          | <b>Incandescent and Magnetic Low Voltage - Forward Phase Dimming</b><br>• Dimmable with the use of most forward phase dimmers • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.<br>Example: Fixture Rating = 10W<br>Dimmer Rating = 600W<br>Equivalent Incandescent Load (EIL) Factor = 50% (.5)<br>(600/10) X .5 = 30 Fixtures per Dimmer |   | <b>Electronic Low Voltage - Reverse Phase Dimming</b><br>• Dimmable with the use of most electronic low voltage dimmers • Electronic low voltage dimmers require a neutral wire in the wall box • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.<br>Example: Fixture Rating = 10W<br>Dimmer Rating = 600W<br>Equivalent Incandescent Load (EIL) Factor = 75% (.75)<br>(600/10) X .75 = 45 Fixtures per Dimmer |   | Universal Voltage (120-277V) Housings<br>0-10V Dimming Control<br>• Dimming range of 100% down to 10% or lower with a minimum load of one fixture.<br>† Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)<br>Note: C-Bus is 25 fixtures per channel. |   |  |
|  |          | Juno Qualified Dimmers  |   |   |   | Juno Qualified Dimmers   |   |  |
| Fixture Series   | WarmDim® | Lutron® Model Numbers:  | Leviton® Model Numbers:   | Whole House Integrated Control Systems:   | Lutron® Model Numbers:  | Leviton® Model Numbers:  | Whole House Integrated Control Systems:   |  |
| 900 LUMEN LED DOWNLIGHT<br>WARMDIM®<br>IC 4"<br>Generation 4 Series      |          | Ariadni® AY* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV* Series<br>Glyder® GLV* Series<br>Nova T® NTLV* Series<br>Skylark® S*/SLV* Series  | IllumaTech™ IPL06* Series<br>Sureslide 6613                     | Lutron® GRAFIK Eye PHPM-PA<br>Lutron® GRAFIK Eye QSGR-RP<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® LP-RPM-4U<br>Lutron® Radio RA2® RRD-6NA*   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series                               | IllumaTech™ IPE04<br>Vizia VPE06-1LX*  |   |  |
| 900 LUMEN LED DOWNLIGHT<br>WARMDIM®<br>5" and 6"<br>Generation 4 Series  |          | Ariadni® AY* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV* Series<br>Glyder® GLV* Series<br>Nova T® NT/NTLV* Series<br>Rotary D Series<br>Skylark® S*/SLV* Series<br>Toggle® TG*   | IllumaTech™ IPL06 Series<br>Sureslide 6613*<br>Sureslide 6633*  | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP*<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® LP-RPM-4U*<br>Lutron® Homeworks® QS HQRD-10ND<br>Lutron® Radio RA2® RRD-10ND<br>Lutron® Radio RA2® RRD-6D   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series                               | IllumaTech™ IPE04<br>Vizia VPE06-1LX*  |   |  |
| 900 LUMEN LED DOWNLIGHT<br>IC 4"<br>Generation 4 Series                  |          | Ariadni® AY* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV* Series<br>Glyder® GLV* Series<br>Nova T® NT/NTLV* Series<br>Rotary D Series<br>Skylark® S*/SLV* Series<br>Toggle® TG* Series  | IllumaTech™ IPL06* Series<br>Sureslide 6633*                    | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP<br>Lutron® Homeworks® QS HQRD-6NA<br>Lutron® Homeworks® QS HQRD-10ND<br>Lutron® Homeworks® RPM-4A*<br>Lutron® Homeworks® RPM-4U<br>Lutron® Radio RA2® RRD-6NA<br>Lutron® Radio RA2® RRD-10ND   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Maestro® MRF2-6ELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IllumaTech™ IPE04* Series<br>Vizia VPE06-1LX*  |   |  |
| 900 LUMEN LED DOWNLIGHT<br>IC 5" and 6"<br>Generation 4 Series           |          | Ariadni® AY*/AYCL* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV*/DVLV* Series<br>Glyder® GLV Series*<br>Lumea® LGCL* Series<br>Nova T® NT Series<br>Nova T® NTLV* Series<br>Rotary D* Series<br>Skylark® Contour CTCL* Series<br>Skylark® S*/SLV* Series<br>Toggle® TGCL* Series   | IllumaTech™ IPL06 Series<br>Sureslide 6613*<br>Sureslide 6633*  | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP*<br>Lutron® Homeworks® LP-RPM-4A<br>Lutron® Homeworks® LP-RPM-4U<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA*   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series                               | IllumaTech™ IPE04* Series<br>Vizia VPE06-1LX*  | Diva® DVTV Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV Series <sup>1</sup><br>Nova® NFTV Series <sup>1</sup>    | IllumaTech™ IP710-DLX Series<br>Schneider Electric C-Bus SLCLE5504TAMP*<br>Lutron® Homeworks® GRX-TVM2 |
| 1000 LUMEN LED DOWNLIGHT<br>4" IC4AL (10LM), TC4AL (10LM), TC4RAL (10LM) |          | Ariadni® AY* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVLV* Series<br>Glyder® GLV* Series<br>Nova T® NT* Series<br>Nova T® NTLV* Series<br>Rotary D Series<br>Skylark® S*/SLV* Series   | IllumaTech™ IPL06* Series<br>Sureslide 6613*<br>Sureslide 6633* | Lutron® GRAFIK Eye QS PHPM-PA*<br>Lutron® GRAFIK Eye QSGR-RP<br>Lutron® Homeworks® LP-RPM-4A*<br>Lutron® Homeworks® LP-RPM-4U*<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA*  | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series                               | IllumaTech™ IPE04* Series<br>Vizia VPE06-1LX*  | Diva® DVTV* Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV* Series <sup>1</sup><br>Nova® NFTV* Series <sup>1</sup> | Lutron® Homeworks® GRX-TVM2*<br>Wattstopper LMRC-211*<br>Crestron DIN-4DIMFLV4                         |
| 900 LUMEN LED DOWNLIGHT<br>IC 5" and 6"<br>Generation 3† Series          |          | Ariadni® AY/AYCL* Series<br>Ceana® CNLV* Series<br>Diva® DV/DVCL*/DVLV* Series<br>Glyder® GLV* Series<br>Lumea® LGCL* Series<br>Nova T® NTLV* Series<br>Skylark® Contour CTCL* Series<br>Skylark® S*/SLV* Series<br>Toggle® TGCL* Series  | IllumaTech™ IPL06 Series<br>Trimatron 6681                      | Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Radio RA2® RRD-10ND<br>Lutron® Radio RA2® RRD-6D<br>Lutron® Radio RA2® RRD-6NA*<br>Schneider Electric C-Bus SLC5504TD4A*   | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series                               | IllumaTech™ IPE04 Series   | Diva® DVTV Series <sup>1</sup><br>GRAFIK Eye QS GRX-TVI<br>Nova T® NTFTV Series <sup>1</sup><br>Nova® NFTV Series <sup>1</sup>    | IllumaTech™ IP710-DLX Series<br>Schneider Electric C-Bus SLCLE5504TAMP*<br>Lutron® Homeworks® GRX-TVM2 |

† J6RL and J6RLE series dimmers listed under dedicated 120V only housing, including incandescent, magnetic low voltage and electronic low voltage.

\* Juno recommended dimmers  
Consult technical services for additional information regarding other dimmer model qualification.



# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

## DEDICATED 120V ONLY HOUSING

**Incandescent and Magnetic Low Voltage - Forward Phase Dimming**

- Dimmable with the use of most forward phase dimmers
- Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL) Factor = 50% (.5)  
 (600/10) X .5 = 30 Fixtures per Dimmer

**Electronic Low Voltage - Reverse Phase Dimming**

- Dimmable with the use of most electronic low voltage dimmers
- Electronic low voltage dimmers require a neutral wire in the wall box
- Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL) Factor = 75% (.75)  
 (600/10) X .75 = 45 Fixtures per Dimmer

## UNIVERSAL VOLTAGE

**Universal Voltage (120-277V) Housings**

0-10V Dimming Control

- Dimming range of 100% down to 10% or lower with a minimum load of one fixture.

<sup>†</sup> Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)

Note: C-Bus is 25 fixtures per channel.

### Juno Qualified Dimmers

| Fixture Series  | DEDICATED 120V ONLY HOUSING  |   |  | UNIVERSAL VOLTAGE   |   |   |
|---|--|---|--|---|---|---|
|   | Lutron® Model Numbers:   | Leviton® Model Numbers:   | Whole House Integrated Control Systems:  | Lutron® Model Numbers:  | Leviton® Model Numbers:                       | Whole House Integrated Control Systems: |
| 1400 LUMEN LED DOWNLIGHT<br>IC 5" and 6"<br>Generation 4 Series | Ariadni® AY*/AYCL* Series<br>Ceana® CNLV* Series<br>Diva® DV*/DVCL*/DVLV* Series<br>Glyder® GLV* Series<br>Lumea® LGCL* Series<br>Nova T® NT*/NTLV* Series<br>Rotary D Series<br>Skylark® Contour CTCL* Series<br>Skylark® S*/SLV* Series<br>Taggler® TGCL* Series | IllumaTech™ IPE04* Series<br>Sureslide 6613-PLW*<br>Sureslide 6633* | Lutron® GRAFIK Eye QS PHPM-PA<br>Lutron® GRAFIK Eye QSQR-RP<br>Lutron® Homeworks® LP-RPM-4A*<br>Lutron® Homeworks® LP-RPM-4U<br>Lutron® Homeworks® QS HQRD-10ND*<br>Lutron® Homeworks® QS HQRD-6NA*<br>Lutron® Homeworks® QS HQRD-6ND<br>Lutron® Radio RA2® RRD-10ND*<br>Lutron® Radio RA2® RRD-6NA*<br>Maestro® WIRELESS MRF2-6ND | Diva® DVELV* Series<br>Faedra® FAELV* Series<br>Maestro® MAELV* Series<br>Nova T® NTELV* Series<br>Skylark® SELV* Series<br>Spacer System® SPSELV* Series | IllumaTech™ IPE04* Series<br>Vizia VPE06-1LX* |   |

\* Juno recommended dimmers  
 Consult technical services for additional information regarding other dimmer model qualification.